



# ECB40W18 Series Application Note December 2024 V15

## ISOLATED DC-DC CONVERTER ECB40W18 SERIES APPLICATION NOTE



### Approved By:

Department	Approved By	Checked By	Written By
Research and Development Department	Jacky	Danny/Tony	Joyce
Design Quality Department	Benny	JoJo	



# ECB40W18 Series

## Application Note December 2024 V15

---

### Contents

1. Introduction .....	3
2. Pin Function Description .....	3
3. Connection for Standard Use .....	4
4. Test Set-Up .....	4
5. Recommend Layout, PCB Footprint and Soldering Information.....	4
6. Features and Functions .....	6
6.1 UVLO (Under Voltage Lock Out) .....	6
6.2 Over Current/Short Circuit Protection .....	6
6.3 Output Over Voltage Protection .....	6
6.4 Over Temperature Protection.....	6
6.5 Remote On/Off .....	7
6.6 Output Voltage Adjustment .....	7
7. Input/Output Considerations .....	9
7.1 Input Capacitance at the Power Module .....	9
7.2 Hold up Time .....	10
7.3 Input Derating Curve .....	10
7.4 Output Ripple and Noise .....	10
7.5 Output Capacitance .....	10
8. Thermal Design.....	11
8.1 Operating Temperature Range .....	11
8.2 Convection Requirements for Cooling .....	11
8.3 Thermal Considerations .....	11
8.4 Power Derating .....	11
8.5 2"x1" Case Heat Sink: .....	13
9. Safety & EMC .....	13
9.1 Input Fusing and Safety Considerations .....	13
9.2 EMC Considerations .....	13
9.3 Suggested Configuration for RIA12 Surge Test.....	22



# ECB40W18 Series

## Application Note December 2024 V15

### 1. Introduction

The ECB40W18 series of DC-DC converters offers 40 watts of output power at output voltages of 5, 12, 15, 24, 48, 54VDC with industry 2"x1"x0.5" package. It has an ultra wide (18:1) input voltage range of 8.5 to 160VDC (72VDC nominal) and 3000VAC reinforced isolation.


Compliant with EN 55032, EN 55035, EN 50155, EN 45545, EN 50121-3-2. High efficiency up to 90%, allowing case operating temperature range of -40°C to 105°C. An optional heat sink is available to extend the full power range of the unit. Very low no load power consumption (10mA), an ideal solution for energy critical systems.

Fully protected against input UVLO (under voltage lock out), output over-current, output over-voltage, over-temperature and continuous short circuit conditions.

The standard control functions include remote **on/off** (positive or negative) and +15% to -20%, except 48 and 54V<sub>out</sub> are +10% to -20% adjustable output voltage.

ECB40W18 series is designed primarily for common railway applications of 24V, 36V, 48V, 72V, 96V, 110V nominal voltage and also suitable for distributed power architectures, telecommunications, battery operated equipment and industrial applications.

### 2. Pin Function Description



No	Label	Function	Description	Reference
1	+Vin	+V Input	Positive Supply Input	<b>Section 7.1/7.2/7.3</b>
2	-Vin	-V Input	Negative Supply Input	<b>Section 7.1/7.2/7.3</b>
3	+Vout	+V Output	Positive Power Output	<b>Section 7.4/7.5</b>
4	Trim	Trim	External Output Voltage Adjustment	<b>Section 6.6</b>
5	-Vout	-V Output	Negative Power Output	<b>Section 7.4/7.5</b>
6	Remote	Remote On/Off	External Remote On/Off Control	<b>Section 6.5</b>
7	Bus	Bus	Pre-Regulator Voltage Output (Option)	<b>Section 7.2</b>




# ECB40W18 Series

## Application Note December 2024 V15

### 3. Connection for Standard Use

The connection for standard use is shown below. External output capacitors (C1) are recommended to reduce output ripple and noise, 1uF ceramic capacitor for all models.



Symbol	Component	Reference
F1, TVS	Input fuse, TVS	<b>Section 9.1</b>
C1	External capacitor on the output side	<b>Section 7.4</b>
Noise Filter	External input noise filter	<b>Section 9.2</b>
Remote On/Off	External remote on/off control	<b>Section 6.5</b>
Trim	External output voltage adjustment	<b>Section 6.6</b>
Heat Sink	External heat sink	<b>Section 5/8.1/8.2/8.3/8.4/8.5</b>

### 4. Test Set-Up

The basic test set-up to measure parameters such as efficiency and load regulation is shown below. When testing the modules under any transient conditions, please ensure that the transient response of the source is sufficient to power the equipment under test. We can calculate:

- Efficiency
- Load regulation and line regulation

The value of efficiency is defined as:

$$\eta = \frac{V_o \times I_o}{V_{in} \times I_{in}} \times 100\%$$

Where:

- $V_o$  is output voltage,
- $I_o$  is output current,
- $V_{in}$  is input voltage,
- $I_{in}$  is input current

The value of load regulation is defined as:

$$Load\ reg. = \frac{V_{FL} - V_{NL}}{V_{NL}} \times 100\%$$

Where:

$V_{FL}$  is the output voltage at full load

$V_{NL}$  is the output voltage at no load


The value of line regulation is defined as:

$$Line\ reg. = \frac{V_{HL} - V_{LL}}{V_{LL}} \times 100\%$$

Where:

$V_{HL}$  is the output voltage of maximum input voltage at full load


$V_{LL}$  is the output voltage of minimum input voltage at full load



ECB40W18 Series Test Setup

### 5. Recommend Layout, PCB Footprint and Soldering Information

The system designer or end user must ensure that metal and other components in the vicinity of the converter meet the spacing requirements for which the system is approved. Low resistance and inductance PCB layout traces are the norm and should be used where possible. Due consideration must also be given to proper low impedance tracks between power module, input and output grounds. The recommended footprints and soldering profiles are shown below.



Standard Module






# ECB40W18 Series

## Application Note December 2024 V15

### 6. Features and Functions



#### 6.1 UVLO (Under Voltage Lock Out)

Input under voltage lockout is standard on the ECB40W18 series unit. The unit will shut down when the input voltage drops below a lower threshold, and the unit will operate when the input voltage goes above the upper threshold.



#### 6.2 Over Current/Short Circuit Protection

All models have internal over current and continuous short circuit protection. The unit operates normally once the fault condition is removed. At the point of current limit inception, the converter will go into hiccup mode protection.





#### 6.3 Output Over Voltage Protection

The over-voltage protection consists of a zener diode or transient voltage suppressors diode to limiting the out voltage.

#### 6.4 Over Temperature Protection

These modules have an over temperature protection circuit to safeguard against thermal damage. Shutdown occurs with the maximum case reference temperature is exceeded. The module will restart when the case temperature falls below over temperature recovery threshold. Please measure case temperature of the center part of aluminum base plate.





# ECB40W18 Series

## Application Note December 2024 V15

### 6.5 Remote On/Off


The ECB40W18 series allows the user to switch the module on and off electronically with the remote **on/off** feature. All models are available in “positive logic” and “negative logic” (optional) versions. The converter turns on if the remote **on/off** pin is high (>3.5Vdc to 160Vdc or open circuit). Setting the pin low (0 to <1.2Vdc) will turn the converter off. The signal level of the remote **on/off** input is defined with respect to ground.

If not using the remote **on/off** pin, leave the pin open (converter will be on). Converter will be turn on in positive mode.


Models with part number suffix “N” are the “negative logic” remote **on/off** version. The unit turns off if the remote **on/off** pin is high (>3.5Vdc to 160Vdc or open circuit). The converter turns on if the **on/off** pin input is low (0 to <1.2Vdc). Note that the converter is off by default.

Logic State (Pin 6)	Negative Logic	Positive Logic
Logic Low	Module on	Module off
Logic High	Module off	Module on

The converter remote **on/off** circuit built-in on input side. The ground pin of input side remote **on/off** circuit is -Vin pin. Inside connection sees below.




Connection Examples See Below




**Remote On/Off Connection Examples**

### 6.6 Output Voltage Adjustment


Output may be externally trimmed +15% to -20%, except 48 and 54V<sub>out</sub> are +10% to -20% with a fixed resistor or an external trim pot as shown (optional). Model specific formulas for calculating trim resistors are available upon request as a separate document.



In order to trim the voltage up or down, one needs to connect the trim resistor either between the trim pin and -V<sub>out</sub> for trim-up or between trim pin and +V<sub>out</sub> for trim-down. The output voltage trim range is +15% to -20%, except 48 and 54V<sub>out</sub> are +10% to -20%. This is shown:



**Trim-up Voltage Setup**



**Trim-down Voltage Setup**

The ECB40W18-72S05 value of R<sub>trim\_up</sub> defined as:

$$R_{trim\_up} = \frac{22.13 - 3.97 \times (V_o - V_{o,nom})}{7.012 \times (V_o - V_{o,nom})} - 3.3 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S12 value of R<sub>trim\_up</sub> defined as:

$$R_{trim\_up} = \frac{120.774}{3 \times (V_o - V_{o,nom})} - 18 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S15 value of R<sub>trim\_up</sub> defined as:

$$R_{trim\_up} = \frac{104.764}{2.285 \times (V_o - V_{o,nom})} - 18 \text{ (K}\Omega\text{)}$$



# ECB40W18 Series

## Application Note December 2024 V15

The ECB40W18-72S24 value of  $R_{trim\_up}$  defined as:

$$R_{trim\_up} = \frac{297.435}{2.43 \times (V_o - V_{o,nom})} - 30 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S48 value of  $R_{trim\_up}$  defined as:

$$R_{trim\_up} = \frac{1235.605}{2.42 \times (V_o - V_{o,nom})} - 56 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S54 value of  $R_{trim\_up}$  defined as:

$$R_{trim\_up} = \frac{1478.43}{2.427 \times (V_o - V_{o,nom})} - 68 \text{ (K}\Omega\text{)}$$

Where:

$R_{trim\_up}$  is the external resistor in K $\Omega$

$V_{o,nom}$  is the nominal output voltage

$V_o$  is the desired output voltage

For example, to trim-up the output voltage of 5V module (ECB40W18-72S05) by 5% to 5.25V,  $R_{trim\_up}$  is calculated as follows:

$$\begin{aligned} R_{trim\_up} &= \frac{22.13 - 3.97 \times (5.25 - 5)}{7.012 \times (5.25 - 5)} - 3.3 \\ &= 8.758 \text{ (K}\Omega\text{)} \end{aligned}$$

The typical value of  $R_{trim\_up}$

Trim up %	5V	12V	15V	24V	48V	54V
	R <sub>trim_up</sub> (K $\Omega$ )					
1%	59.254	317.484	287.656	480.005	1007.710	1060.073
2%	27.694	149.742	134.828	225.003	475.855	496.037
3%	17.174	93.828	83.885	140.002	298.570	308.024
4%	11.914	65.871	58.414	97.501	209.927	214.018
5%	8.758	49.097	43.131	72.001	156.742	157.615
6%	6.654	37.914	32.943	55.001	121.285	120.012
7%	5.151	29.926	25.665	42.858	95.959	93.153
8%	4.024	23.936	20.207	33.751	76.964	73.009
9%	3.147	19.276	15.962	26.667	62.190	57.341
10%	2.446	15.548	12.566	21.001	50.371	44.807
11%	1.872	12.499	9.787	16.364		
12%	1.394	9.957	7.471	12.500		
13%	0.989	7.806	5.512	9.231		
14%	0.643	5.963	3.833	6.429		
15%	0.342	4.366	2.377	4.000		

The ECB40W18-72S05 value of  $R_{trim\_down}$  defined as:

$$R_{trim\_down} = \frac{41.995 - 16.792 \times (V_{o,nom} - V_o)}{7.012 \times (V_{o,nom} - V_o)} - 3.3 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S12 value of  $R_{trim\_down}$  defined as:

$$R_{trim\_down} = \frac{206.151}{3 \times (V_{o,nom} - V_o)} - 27.081 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S15 value of  $R_{trim\_down}$  defined as:

$$R_{trim\_down} = \frac{207.025}{2.285 \times (V_{o,nom} - V_o)} - 27.1 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S24 value of  $R_{trim\_down}$  defined as:

$$R_{trim\_down} = \frac{624.1}{2.43 \times (V_{o,nom} - V_o)} - 45.8 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S48 value of  $R_{trim\_down}$  defined as:

$$R_{trim\_down} = \frac{2265.025}{2.42 \times (V_{o,nom} - V_o)} - 86.1 \text{ (K}\Omega\text{)}$$

The ECB40W18-72S54 value of  $R_{trim\_down}$  defined as:

$$R_{trim\_down} = \frac{3240}{2.427 \times (V_{o,nom} - V_o)} - 104 \text{ (K}\Omega\text{)}$$

Where:

$R_{trim\_down}$  is the external resistor in K $\Omega$

$V_{o,nom}$  is the nominal output voltage

$V_o$  is the desired output voltage

For example: to trim-down the output voltage of 12V module (ECB40W18-72S12) by 5% to 11.4V,  $R_{trim\_down}$  is calculated as follows:

$$R_{trim\_down} = \frac{206.151}{3 \times (12 - 11.4)} - 27.081 = 87.448 \text{ (K}\Omega\text{)}$$



# ECB40W18 Series



## Application Note December 2024 V15

The typical value of  $R_{trim\_down}$

Trim down %	5V	12V	15V
	$R_{trim\_down}$ (K $\Omega$ )		
1%	114.089	545.562	576.912
2%	54.197	259.241	274.906
3%	34.233	163.800	174.237
4%	24.251	116.080	123.903
5%	18.262	87.448	93.702
6%	14.269	68.360	73.569
7%	11.417	54.725	59.187
8%	9.278	44.500	48.401
9%	7.614	36.546	40.012
10%	6.284	30.184	33.301
11%	5.195	24.978	27.810
12%	4.287	20.639	23.234
13%	3.519	16.969	19.362
14%	2.861	13.822	16.044
15%	2.291	11.095	13.167
16%	1.792	8.709	10.651
17%	1.351	6.604	8.430
18%	0.960	4.733	6.456
19%	0.610	3.058	4.690
20%	0.294	1.551	3.101

Trim down %	24V	48V	54V
	$R_{trim\_down}$ (K $\Omega$ )		
1%	1024.330	1863.818	2368.188
2%	489.265	888.859	1132.094
3%	310.910	563.873	720.063
4%	221.733	401.380	514.047
5%	168.226	303.884	390.438
6%	132.555	238.886	308.031
7%	107.076	192.460	249.170
8%	87.966	157.640	205.023
9%	73.103	130.558	170.688
10%	61.213	108.892	143.219
11%	51.485	91.165	120.744
12%	43.378	76.393	102.016
13%	36.518	63.894	86.168
14%	30.638	53.180	72.585
15%	25.542	43.895	60.813
16%	21.083	35.770	50.512
17%	17.149	28.601	41.423
18%	13.652	22.229	33.344
19%	10.523	16.527	26.115
20%	7.707	11.396	19.609


ECB40W18 series input range and output trim voltage curve are shown below.



## 7. Input/Output Considerations

### 7.1 Input Capacitance at the Power Module

The converters must be connected to low AC source impedance. To avoid problems with loop stability source inductance should be low. Also, the input capacitors ( $C_{in}$ ) should be placed close to the converter input pins to decouple distribution inductance. However, the external input capacitors are chosen for suitable ripple handling capability. Low ESR capacitors are good choice. Circuit as shown as below represents typical measurement methods for reflected ripple current.  $C_1$  and  $L_1$  simulate a typical DC source impedance. The input reflected-ripple current is measured by current probe to oscilloscope with a simulated source Inductance ( $L_1$ ).




$L_1$ : 12 $\mu$ H  
 $C_1$ : None  
 $C_{in}$ : 120 $\mu$ F ESR<0.2ohm @100KHz



# ECB40W18 Series Application Note December 2024 V15

## 7.2 Hold up Time

Hold up time is defined as the duration of time that the DC/DC converter output will remain active following a loss of input power. The Bus pin is for hold up time function. It is designed to work with an external circuit comprises C5. When input power supply is interrupted, the ECB40W18 series use the energy stored in C5 to support operation. A typical configuration shows as below.




C1: None

If hold up time function is not needed, please remove the component (C5). This function provides energy that maintains the DC-DC converter in operation for 10mS and 30mS hold up time. The capacity (C5) in the application is recommended as below.


C5		V <sub>in</sub>					
		24V	36V	48V	72V	96V	110V
For 10 mS	C5	2600uF	1900uF	1900uF	1900uF	1900uF	1900uF
For 30 mS		7700uF	5700uF	5700uF	5700uF	5700uF	5700uF

## 7.3 Input Derating Curve

ECB40W18 series has derating by Input Voltage is required shown below.



## 7.4 Output Ripple and Noise



Note:

C1: None


C2: 1uF ceramic capacitor

Output ripple and noise measured with 1uF ceramic capacitor across output, A 20 MHz bandwidth oscilloscope is normally used for the measurement.

The conventional ground clip on an oscilloscope probe should never be used in this kind of measurement. This clip, when placed in a field of radiated high frequency energy, acts as an antenna or inductive pickup loop, creating an extraneous voltage that is not part of the output noise of the converter.



Another method is shown in below, in case of coaxial-cable/BNC is not available. The noise pickup is eliminated by pressing scope probe ground ring directly against the -V<sub>out</sub> terminal while the tip contacts the +V<sub>out</sub> terminal. This makes the shortest possible connection across the output terminals.



## 7.5 Output Capacitance

The ECB40W18 series converters provide unconditional stability with or without external capacitors. For good transient response, low ESR output capacitors should be located close to the point of load (<100mm). PCB design emphasizes low resistance and inductance tracks in consideration of high current applications. Output capacitors with their associated ESR values have an impact on loop stability and bandwidth. Cincon's converters are designed to work with load capacitance to see technical specifications.



# ECB40W18 Series

## Application Note December 2024 V15

### 8. Thermal Design

#### 8.1 Operating Temperature Range

The ECB40W18 series converters can be operated within a wide case temperature range of -40°C to 105°C. Consideration must be given to the derating curves when ascertaining maximum power that can be drawn from the converter. The maximum power drawn from models is influenced by usual factors, such as:

- Input voltage range
- Output load current
- Forced air or natural convection
- Heat sink optional

#### 8.2 Convection Requirements for Cooling

To predict the approximate cooling needed for the 2"×1" module, refer to the power derating curves in **section 8.4**. These derating curves are approximations of the ambient temperatures and airflows required to keep the power module temperature below its maximum rating. Once the module is assembled in the actual system, the module's temperature should be monitored to ensure it does not exceed 105°C as measured at the center of the top of the case (thus verifying proper cooling).


#### 8.3 Thermal Considerations

The power module operates in a variety of thermal environments; however, sufficient cooling should be provided to help ensure reliable operation of the unit. Heat is removed by conduction, convection, and radiation to the surrounding environment. The example is presented in **section 8.4**. The power output of the module should not be allowed to exceed rated power ( $V_{o\_set} \times I_{o\_max}$ ).

#### 8.4 Power Derating

The operating case temperature range of ECB40W18 series is -40°C to +105°C. When operating the ECB40W18 series, proper derating or cooling is needed. The maximum case temperature under any operating condition should not exceed 105°C.

The following de-rating curves of ECB40W18-72S12 without heat sink and with heat sink.




AIR FLOW RATE	TYPICAL $R_{ca}$
Natural Convection 20ft./min. (0.1m/s)	9.2 °C/W
100 ft./min. (0.5m/s)	8.2 °C/W
200 ft./min. (1.0m/s)	6.4 °C/W
300 ft./min. (1.5m/s)	5.8 °C/W
400 ft./min. (2.0m/s)	4.9 °C/W



# ECB40W18 Series

## Application Note December 2024 V15

**ECB40W18-72S12 Derating Curve  
with Heatsink BL150G ( $V_{in}=72V$ )**



AIR FLOW RATE	TYPICAL $R_{ca}$
Natural Convection 20ft./min. (0.1m/s)	5.62 °C/W
100 ft./min. (0.5m/s)	4.94 °C/W
200 ft./min. (1.0m/s)	3.52 °C/W
300 ft./min. (1.5m/s)	3.14 °C/W
400 ft./min. (2.0m/s)	2.38 °C/W

**Example:**

The ECB40W18-72S12 operating at nominal line voltage, an output current of 3.333A, and a maximum ambient temperature of 70°C.

**Solution:**

**Given:**  $V_{in}=72V_{dc}$ ,  $V_o=12V_{dc}$ ,  $I_o=3.333A$

**Determine power dissipation ( $P_d$ ):**  $P_d=P_i-P_o=P_o(1-\eta)/\eta$ ,  $P_d=12 \times 3.333 \times (1-0.90)/0.90=4.45Watts$

**Determine airflow:** Airflow=200ft./min.

**Check power derating curve:** Given:  $P_d=4.45W$  and  $T_a=70^\circ C$

**Verify:**

Maximum temperature rise is  $\Delta T=P_d \times R_{ca}=4.45 \times 6.4=28.48^\circ C$

Maximum case temperature is  $T_c=T_a + \Delta T=98.48^\circ C < 105^\circ C$

**Where:**

The  $R_{ca}$  is thermal resistance from case to ambient environment.

$T_a$  is ambient temperature and  $T_c$  is case temperature.

**Example with heat sink BL150G (M-C1677):**

The ECB40W18-72S12 operating at nominal line voltage, an output current of 3.333A, and a maximum ambient temperature of 80°C.

**Solution:**

**Given:**  $V_{in}=72V_{dc}$ ,  $V_o=12V_{dc}$ ,  $I_o=3.333A$

**Determine power dissipation ( $P_d$ ):**  $P_d= P_i-P_o=P_o(1-\eta)/\eta$ ,  $P_d=12 \times 3.333 \times (1-0.90)/0.90=4.45Watts$

**Determine airflow:** Airflow=200 ft./min

**Check above power derating curve:** Given:  $P_d=4.45W$  and  $T_a=80^\circ C$

**Verify:**

Maximum temperature rise is  $\Delta T= P_d \times R_{ca}=4.45 \times 3.52=15.66^\circ C$

Maximum case temperature is  $T_c=T_a+\Delta T=95.66^\circ C < 105^\circ C$

**Where:**

The  $R_{ca}$  is thermal resistance from case to ambient environment

$T_a$  is ambient temperature and  $T_c$  is case temperature



# ECB40W18 Series Application Note December 2024 V15


## 8.5 2"x1" Case Heat Sink:

Heat sinks assembly [refer to Datasheet-Thermal](#)

## 9. Safety & EMC

### 9.1 Input Fusing and Safety Considerations

The ECB40W18 series converters have no internal fuse. In order to achieve maximum safety and system protection, always use an input line fuse. We recommended a 6.3A time delay fuse for all models. It is recommended that the circuit has a transient voltage suppressor diode (TVS) across the input terminal to protect the unit against surge or spike voltage and input reverse voltage (as shown).



The external input capacitor (Cin) and transient voltage suppressor diode (TVS) are required if ECB40W18 series has to meet EN 61000-4-4, EN 61000-4-5.


Cin: 150uF/200V (RUBYCON BXW series) aluminum capacitor is recommended.

TVS: SMDJ180A transient voltage suppressor is recommended.

### 9.2 EMC Considerations

EMI Test standard: EN 55032 Class A, EN 50121-3-2

Test Condition: Input Voltage: 110Vdc, Output Load: Full Load





## ECB40W18 Series

### Application Note December 2024 V15

Model Number	ECB40W18-72S05	ECB40W18-72S12	ECB40W18-72S15	ECB40W18-72S24	ECB40W18-72S48	ECB40W18-72S54
C103	2.2uF/450V			1uF/450V		
C104	1uF/450V					
C106	150uF/200V					
CY1	220pF					
CY3, CY4	2200pF	1000pF	2200pF	2200pF	2200pF	2200pF
CY7, CY9	4700pF					
CY11, CY12	2200pF	1500pF	4700pF	4700pF	4700pF	4700pF
CY13	NC				4700pF	4700pF
L101	1mH (F1407-102BL-G)					
L102	5mH (SP21030T-LF)					

**Note:**

- C103, C104: Metallized polypropylene film capacitor, FPS4 series or equivalent
- C106: RUBYCON BXW series aluminum capacitor or equivalent
- CY1: TDK Y1 or Y2 capacitor or equivalent
- CY3, CY4, CY7, CY9, CY11, CY12, CY13: TDK Y1 capacitor or equivalent
- L101: F1407-102BL-G, SENDPOWER or equivalent
- L102: SP21030T-LF, SENDPOWER or equivalent




# ECB40W18 Series

## Application Note December 2024 V15


### Input Conducted Emission (EN55032 Class A):

ECB40W18-72S05

Line




Neutral




ECB40W18-72S12

Line




Neutral




ECB40W18-72S15

Line




Neutral




ECB40W18-72S24

Line



Neutral






# ECB40W18 Series


## Application Note December 2024 V15

ECB40W18-72S48

Line




Neutral




ECB40W18-72S54

Line



Neutral






# ECB40W18 Series

## Application Note December 2024 V15


### Input Conducted Emission (EN50121-3-2):

ECB40W18-72S05

Line




Neutral




ECB40W18-72S12

Line




Neutral




ECB40W18-72S15

Line




Neutral




ECB40W18-72S24

Line



Neutral






# ECB40W18 Series


## Application Note December 2024 V15

ECB40W18-72S48

Line




Neutral




ECB40W18-72S54

Line



Neutral






# ECB40W18 Series

## Application Note December 2024 V15


### Output Conducted Emission (EN50121-3-2):

ECB40W18-72S05

Positive




Negative




ECB40W18-72S12

Positive




Negative




ECB40W18-72S15

Positive




Negative




ECB40W18-72S24

Positive



Negative






# ECB40W18 Series


## Application Note December 2024 V15

ECB40W18-72S48

Positive




Negative




ECB40W18-72S54

Positive




Negative




### Radiated Emission (EN55032 Class A / EN50121-3-2):

ECB40W18-72S05

Horizontal




Vertical




ECB40W18-72S12

Horizontal



Vertical






# ECB40W18 Series


## Application Note December 2024 V15

### ECB40W18-72S15

Horizontal




Vertical




### ECB40W18-72S24

Horizontal




Vertical




### ECB40W18-72S48

Horizontal




Vertical



### ECB40W18-72S54

Horizontal



Vertical

